

FMRX

FM Radio 87.5-108.5MHz FM Radio Receive Collinear

The FMRX is an economical and effective fixed position solution to those seeking to improve their FM radio reception at home or in the office, particularly in situations where signal strength indoors is poor.

Mounting clamps, coaxial feeder cables, connectors and other installation accessories are all available separately.

| Specifications | FMRX |
|---------------------------------|--|
| Construction | Black radome, aluminium ferrule and galvanised 'L' bracket |
| Frequency | FM 87.5-108.5MHz |
| Bandwidth | Full band |
| Tuning | Factory |
| Gain | 0 dBd (receive only) |
| Cable | 6 metres of RG58 stranded (side exit) |
| Cable termination | To rear panel of FM radio tuner |
| Height | 2.06 metres |
| Weight | 500 grams |
| Mounting Accessories (supplied) | Screw 'L' bracket to vertical surface |
| Mounting Position (recommended) | Mount as high on your structure, mast or pole as possible using the 'L' bracket to extend past gutters or overhangs. |

